

## DMPS Lite™ 4K Multiformat 2x1 AV Switch and Receiver



- 4K/60 4:2:0 capability
- One DM Lite® port for interoperability with one DM Lite transmitter
- One HDMI® input
- One HDMI output with 4K scaler
- Gigabit Ethernet port
- Stereo line level audio output
- IR, RS-232, relay, and I/O control ports
- CEC (Consumer Electronics Control) capability
- Automatic switching of inputs
- EDID management
- HDCP management including HDCP 2.2 support
- Built-in web interface for easy configuration and monitoring
- Compatibility with Crestron® 3-Series® or later control systems
- .AV Framework™ technology support
- XiO Cloud® service support
- Native integration with Cisco Webex® and Touch 10 devices
- 100-240 VAC power pack included
- Compact surface-mountable design

The Crestron HD-RX-4K-210-C-E is a DMPS Lite™ multiformat AV switch and receiver that provides HDMI® video switching and audio presentation capabilities in areas such as conference rooms and classrooms. Compatible with all DM Lite® transmitters, the HD-RX-4K-210-C-E provides one DM Lite input for connection to one transmitter. A CATx (CAT5e or higher) twisted pair cable connects a transmitter to the HD-RX-4K-210-C-E for the transmission of HDMI signals. For resolutions up to 2K, the maximum transmission distance is 230 ft (70 m). For higher resolutions up to 4K, the maximum transmission distance is 130 ft (40 m).<sup>1</sup>

**NOTE:** Power is transmitted over the CATx cable that connects the HD-RX-4K-210-C-E to a DM Lite transmitter.

In addition to one DM Lite input, the HD-RX-4K-210-C-E provides one HDMI input that can be connected to a local AV source or to an optional Crestron® media presentation wall plate ([MP-WP152](#) or [MPI-WP150](#) Series, sold separately).

### Automatic Switching of Inputs

Automatic switching between the DM Lite input and HDMI input can occur based on the last connected input or on the routing priority assigned to each input. Switching behavior is configurable using the web interface or programmable using a Crestron control system. In addition, input selection push buttons on the front panel of the HD-RX-4K-210-C-E enable the desired input to be selected manually.

### HDMI Output with 4K Scaler

A single HDMI output with a built-in scaler connects to a display or other device with an HDMI input. Input resolutions are automatically scaled to match the native resolution of the display device, resulting in optimal image quality. For applications requiring comprehensive EDID management, the web interface can be used to ensure that every input is displayed at its optimal resolution and format. Input resolutions up to 4K60 4:2:0 are supported.

### Device Control

Equipped with onboard control ports, the HD-RX-4K-210-C-E can control various devices in a room. The COM (RS-232) port and CEC over the HDMI output can enable the display device to be turned on or off automatically without the use of a control system. With the use of a control system, the IR port can also control the display device. Two relay ports are provided for controlling a projection screen and other low-voltage contact-closure activated equipment. Two Versiport I/O ports enable the integration of devices such as power sensors and motion detectors. An Ethernet port connection to a LAN also provides control by enabling use of the built-in web interface as well as connection to a control system.

**NOTE:** The IR, COM, and Ethernet ports cannot be used to extend signals over a DM Lite connection.

## DMPS Lite™ 4K Multiformat 2x1 AV Switch and Receiver

### Native Integration with Cisco Webex® and Touch 10 Devices

Native integration of the Cisco API enables source inputs of the HD-RX-4K-210-C-E to be added to a compatible Cisco Webex video conference system that is controlled by a Cisco Touch 10 control unit. Eliminating the need for control system programming, integration with Cisco® devices is accomplished by using the Crestron Configuration tool, which is hosted on the Crestron website at [configuration.crestron.com](http://configuration.crestron.com). Configuration includes the selection of the desired Crestron and Cisco hardware models and the assignment of HD-RX-4K-210-C-E input names and icons for use on the Cisco Touch 10 screen. The resulting configuration file is then downloaded from the website and loaded to the HD-RX-4K-210-C-E using the HD-RX-4K-210-C-E web interface. Communication is established between the HD-RX-4K-210-C-E and Cisco devices, enabling the Cisco Touch 10 to display and control the additional HD-RX-4K-210-C-E inputs.

### Compact Design

Compact in design, the HD-RX-4K-210-C-E can be mounted onto a flat surface such as a wall or attached to the underside of a table. The device can also be mounted to a rack rail.

### Specifications

#### Video

**Switcher:** 2x1 auto-switching or manual, audio-follows-video, Crestron Auto-Locking® and QuickSwitch HD™ technologies

**Scaler (HDMI Output):** 4K video scaler with intelligent frame rate conversion, Deep Color support, content-adaptive noise reduction, 3:2/2:2 pull-down detection and recovery

**Input Signal Types:** HDMI with Deep Color and 4K (DVI and Dual-Mode DisplayPort™ interface compatible<sup>2</sup>) on Input 1, DM Lite with Deep Color and 4K on Input 2

**Output Signal Types:** HDMI with Deep Color and 4K (DVI compatible<sup>3</sup>)

**Copy Protection:** HDCP 2.2

**Maximum Resolutions:** Common resolutions are listed below for the HDMI and DM Lite inputs.

Scan Type	Resolution	Frame Rate	Color Sampling	Color Depth
Progressive	4096x2160 DCI 4K and 3840x2160 4K UHD	24 Hz	4:4:4	30 bit
		30 Hz	4:4:4	24 bit
		30 Hz	4:2:2	36 bit
		60 Hz	4:2:0	24 bit
	2560x1600 WQXGA	60 Hz	4:4:4	36 bit
	1920x1080 HD 1080p	60 Hz	4:4:4	36 bit

#### NOTES:

- Custom resolutions are supported at pixel clock rates up to 300 MHz.
- Interlaced video sources are not supported.

#### Scaler Output Resolutions, HDMI:

Auto (EDID preferred), 1280x720p@50Hz (720p50), 1280x720p@60Hz (720p60), 1920x1080i@25Hz (1080i25), 1920x1080i@30Hz (1080i30), 1920x1080p@30Hz (1080p30), 1920x1080p@25Hz (1080p25), 1920x1080p@24Hz (1080p24), 1920x1080p@50Hz (1080p50), 1920x1080p@60Hz (1080p60), 3840x2160p@24Hz, 3840x2160p@25Hz, 3840x2160p@30Hz, 4096x2160p@24Hz, 4096x2160p@25Hz, 4096x2160p@30Hz, 3840x2160p@50Hz, 3840x2160p@60Hz, 4096x2160p@50Hz, 4096x2160p@60Hz

## DMPS Lite™ 4K Multiformat 2x1 AV Switch and Receiver

### Audio

**Input Signal Types:** HDMI (Dual-Mode DisplayPort compatible<sup>2</sup>), DM Lite

**Output Signal Types:** HDMI, stereo analog

**Digital Formats:** 2-channel LPCM

**Analog Formats:** Stereo 2-channel

**Digital-to-Analog Conversion:** 24-bit 48 kHz

**Output Impedance:** 200 ohms balanced, 100 ohms unbalanced

**Maximum Output Level:** 4 Vrms balanced, 2 Vrms unbalanced

**Output Volume:** -80 to +20 dB level adjustment range plus Mute

**Mute:** Enable or disable independently for HDMI and analog audio output

**Analog Output Performance:**

- Frequency Response: 20 Hz to 20 kHz ±0.5 dB
- S/N Ratio: >95 dB @ 10 dBV, 20 Hz to 20 kHz, A-weighted
- THD+N: <0.005% @ 1 kHz and 10 dBV
- Stereo Separation: 20 Hz to 20 kHz ≤80 dB

**Acoustic Noise:** Not applicable (fanless)

### Communications

**Ethernet:** 100/1000 Mbps, auto-switching, auto-negotiating, auto-discovery, full/half duplex, CIP, DHCP, web browser setup and control

**RS-232:** 2-way device control and monitoring up to 115.2k baud with hardware and software handshaking

**IR:** 1-way device control via infrared up to 60 kHz

**HDMI:** HDCP 2.2, EDID, CEC

**DM Lite:** HDCP 2.2, EDID

### Connectors

**HDMI INPUT 1:** (1) HDMI Type A connector, female; HDMI digital video/audio input; DVI and Dual-Mode DisplayPort interface compatible<sup>2</sup>

**DM Lite INPUT 2:** (1) 8-pin RJ-45 yellow connector, female, shielded; DM Lite input port for connection to a DM Lite transmitter

**HDMI OUTPUT:** (1) HDMI Type A connector, female; HDMI digital video/audio output; DVI compatible<sup>3</sup>

**NOTE:** CEC over the HDMI output provides Power On/Off control of the display device without a control system or full programmable control of any device with a control system.

**AUDIO L/R:** (1) 5-pin 3.5 mm detachable terminal block; Balanced/unbalanced stereo line-level audio output; Maximum Output Level: 4 Vrms balanced, 2 Vrms unbalanced; Output Impedance: 200 ohms balanced, 100 ohms unbalanced

**Ethernet:** (1) 8-pin RJ-45 connector, female; 100BASE-TX/1000BASE-T Ethernet port

**I/O 1-2:** (2) 2-pin detachable terminal blocks; Comprised of 2 Versiport digital input/output or analog input ports (referenced to GND); Digital Input: Rated to 0-24 VDC, input impedance 20k ohms, logic threshold >3.125 V low/0 and <1.875 V high/1; Digital Output: 250 mA sink from maximum 24 VDC, catch diodes for use with real world loads; Analog Input: Rated for 0-10 VDC, protected to 24 VDC maximum, input impedance 21k ohms with pull-up resistor disabled; Programmable 5 V, 2k ohms pull-up resistor per pin

**RELAY 1-2:** (2) 2-pin detachable terminal blocks; Comprised of 2 normally open, isolated relays; Rated 1 A, 30 VAC/VDC; MOV arc suppression across contacts

**IR:** (1) 2-pin 3.5 mm detachable terminal block; IR output control port; supports IR up to 60 kHz; [IRP2](#) emitter sold separately

**NOTE:** The IR port provides Power On/Off control of the display device with the use of a control system.

**COM:** (1) 5-pin 3.5 mm detachable terminal block; Bidirectional RS-232 port; Supports RS-232 up to 115.2k baud with hardware and software handshaking

**NOTE:** The COM port provides Power On/Off control of the display device without a control system or full programmable control of any device with a control system.

**24V 1.25A:** (1) 2.1 x 5.5 mm DC power connector; 24 VDC power input; [PW-2412WU](#) power pack included

**NOTE:** The power pack powers both the HD-RX-4K-210-C-E and the connected DM Lite transmitter. A power pack must not be connected to both devices simultaneously.

**SERVICE:** (1) USB Type A connector, female; For factory use only

### Controls and Indicators

**PWR:** (1) LED, indicates that power is being applied to the HD-RX-4K-210-C-E from the power pack connected to either the HD-RX-4K-210-C-E or the transmitter. Amber indicates that the HD-RX-4K-210-C-E is booting. Green indicates that the HD-RX-4K-210-C-E is operational.

## DMPS Lite™ 4K Multiformat 2x1 AV Switch and Receiver

**INPUT 1-2:** (2) Push buttons for manual input selection and (2) LEDs. Green indicates that video is switched. Amber indicates that video is detected but is not switched.

**AUTO:** (1) Push button to enable or disable automatic switching, and (1) green LED to indicate that automatic switching is enabled

**SETUP:** (1) Red LED and (1) push button for display of IP address on the HDMI output

**DM Lite:** (2) LEDs on RJ-45 connector. Green indicates that a DM Lite link is established. Flashing amber indicates non-HDCP video and solid amber indicates HDCP video.

**Ethernet:** (2) LEDs on RJ-45 connector. Green indicates that an Ethernet link is established. Flashing amber indicates Ethernet activity.

### Power

#### Power Pack (Included):

Input: 100-240 VAC, 50/60 Hz  
Output: 1.25 A @ 24 VDC  
Model: [PW-2412WU](#)

**NOTE:** The power pack powers both the HD-RX-4K-210-C-E and the connected DM Lite transmitter. A power pack must not be connected to both devices simultaneously.

**Power Consumption:** 9 W typical

### Environmental

**Temperature:** 32° to 104° F (0° to 40° C)

**Humidity:** 10% to 90% RH (non-condensing)

**Heat Dissipation:** 30.7 BTU/hr

### Enclosure

**Chassis:** Metal, black finish, vented sides, 2 mounting flanges attached

**Mounting:** Surface or rack rail mount

### Dimensions

**Height:** 5.11 in. (130 mm)

**Width:** 10.53 in. (268 mm) with mounting flanges attached

**Depth:** 1.10 in. (28 mm)

### Weight

2.3 lb (1.05 kg) with mounting flanges attached

### Compliance

**Regulatory Model:** M1845001

UL® Listed for US and Canada, CE, IC, FCC Part 15 Class B digital device

### Model

**HD-RX-4K-210-C-E:** DMPS Lite™ 4K Multiformat 2x1 AV Switch and Receiver

### Included Accessory

**PW-2412WU:** Wall Mount Power Pack, 24 VDC, 1.25 A, 2.1 mm, Universal

### Available Accessories

For a list of available accessories, visit the [HD-RX-4K-210-C-E](#) product page.

#### Notes:

1. For the DM Lite connection, use Crestron DM-CBL-8G, Crestron DM-CBL-ULTRA, or third-party CAT5e or higher cable. To safeguard against unpredictable environmental electrical noise that may impact performance at resolutions above 1080p, shielded cable and connectors are recommended for all applications and are required when bundling multiple cables in a wire run. Wire and cables sold separately. DM Lite ports are not compatible with DigitalMedia 8G+, HDBaseT®, PoE, or PoDM technology or any other type of CATx based interface or network.
2. The HDMI input requires an appropriate adapter or interface cable to accommodate a DVI or Dual-Mode DisplayPort signal. [CBL-HDI-DVI](#) interface cables are available separately.
3. The HDMI output requires an appropriate adapter or interface cable to accommodate a DVI signal. [CBL-HDI-DVI](#) interface cables are available separately.

This product may be purchased from select authorized Crestron dealers and distributors. To find a dealer or distributor, please contact the Crestron sales representative for your area. A list of sales representatives is available online at [www.crestron.com/How-To-Buy/Find-a-Representative](http://www.crestron.com/How-To-Buy/Find-a-Representative) or by calling 855-263-8754.

This product is covered under the Crestron standard limited warranty. Refer to [www.crestron.com/warranty](http://www.crestron.com/warranty) for full details.

The specific patents that cover Crestron products are listed online at [patents.crestron.com](http://patents.crestron.com).

Certain Crestron products contain open source software. For specific information, please visit [www.crestron.com/opensource](http://www.crestron.com/opensource).

## DMPS Lite™ 4K Multiformat 2x1 AV Switch and Receiver

Crestron, the Crestron logo, .AV Framework, 3-Series, Auto-Locking, DigitalMedia, DigitalMedia 8G+, DM Lite, DMPS Lite, QuickSwitch HD, and XiO Cloud are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Cisco and Cisco Webex are either trademarks or registered trademarks of Cisco Technology, Inc. in the United States and/or other countries. HDBaseT is either a trademark or registered trademark of the HDBaseT Alliance in the United States and/or other countries. HDMI and the HDMI logo are either trademarks or registered trademarks of HDMI Licensing LLC in the United States and/or other countries. Microsoft and Azure are either trademarks or registered trademarks of Microsoft Corporation in the United States and/or other countries. UL is either a trademark or registered trademark of Underwriters Laboratories, Inc. in the United States and/or other countries. DisplayPort is either a trademark or registered trademark of Video Standards Association in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography.

### HDMI

Specifications are subject to change without notice.

©2021 Crestron Electronics, Inc.

Rev 11/15/21

## DMPS Lite™ 4K Multiformat 2x1 AV Switch and Receiver

