

FreeSpeech® IR Beacon Sensor

Mounts to the ceiling to receive the infrared beacon signal from any FreeSpeech® [MP-FSMIC](#) wireless microphone^[1]. Connects to a [MP-FS-RX1](#) or [MP-FS-RX2](#) receiver^[1] to sense when the wireless microphone is in the room and turned on.

SPECIFICATIONS

Wireless Communications

IR: 38 kHz

Range (typical): 50 ft (15 m) indoor, subject to site-specific conditions

Connectors

T,R,S: (1) 3-pin captive terminal block;
Interface to MP-FS-RX1 or MP-FS-RX2 receiver^[1]

Environmental

Temperature: 41° to 104°F (5° to 40°C)

Humidity: 10% to 90% RH (non-condensing)

Enclosure

Plastic, white textured, mounts to ceiling or other flat surface

Dimensions

Height: 1.25 in (32 mm)

Diameter: 4.34 in (111 mm)

Weight

3.3 oz (92 g)

MODELS & ACCESSORIES

Available Models

MP-FSIR-W-T-1: FreeSpeech® IR Beacon Sensor, White Textured



Notes:

- Item(s) sold separately or as part of a [MP-FS100_PAK](#) or [MP-FS200_PAK](#) system package.

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/salesreps or by calling 800-237-2041.

Specifications subject to change without notice. Crestron is not responsible for errors in typography or photography.

The specific patents that cover Crestron products are listed online at: patents.crestron.com.

Crestron, FreeSpeech, and the Crestron logo are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. ©2012 Crestron Electronics, Inc.

MP-FSIR FreeSpeech® IR Beacon Sensor

