

DM Lite® 4K60 4:4:4 Transmitter for HDMI® and Analog Audio Signal Extension over CATx Cable, Wall Plate



- Interoperability with a DM Lite® receiver or DMPS Lite™ switcher
- Point-to-point extension of HDMI and analog audio signals over a CAT5e or higher cable
- DM Lite transmission distance up to 130 ft (40 m) for UHD and 4K signals or up to 230 ft (70 m) for 1080p, WUXGA, and 2K signals
- 4K60 4:4:4 capability
- HDR10, HDR10+, and Dolby Vision® video formats
- Compliance with HDCP 2.3
- Analog audio embedding
- CEC (Consumer Electronics Control) pass-through capability
- EDID pass-through capability
- One-gang wall plate design with black finish
- Decorator style faceplate required (FP-G Series sold separately)
- Power from the remote DM Lite receiver (surface mountable only) or DMPS Lite switcher

The HD-TXA-4KZ-101-1G is a DM Lite® 4K60 4:4:4 wall plate transmitter designed to interoperate with a DM Lite® receiver or DMPS Lite™ switcher for the transmission of HDMI® and analog audio signals. A CAT5e or higher twisted pair cable is used to connect the HD-TXA-4KZ-101-1G to the DM Lite receiver or DMPS Lite switcher. For 1080p, WUXGA, and 2K signals, a cable length of up to 230 ft (70 m) is supported. For UHD and 4K signals, a cable length of up to 130 ft (40 m) is supported.¹

The HD-TXA-4KZ-101-1G is available in black (model HD-TXA-4KZ-101-1G-B).

Interoperability with a DM Lite Receiver or DMPS Lite Switcher

The DM Lite output port of the HD-TXA-4KZ-101-1G must be connected to a DM Lite input port of a DM Lite receiver or DMPS Lite switcher. Examples of supported DM Lite 4K60 4:4:4 receivers are the HD-RX-4KZ-101, HD-RXA-4KZ-101, HD-RXC-4KZ-101, and HD-RXCA-4KZ-101. Supported DM Lite 4K60 4:2:0 receivers are the HD-RX-101-C-E, HD-RXC-101-C-E, HD-RX-201-C-E, HD-RX-101-C-1G-E, and HD-RXC-101-C-1G-E. Supported DMPS Lite switchers are the HD-PS622, HD-PS621, HD-PS402, HD-PS401, and HD-RX-4K-210-C-E(-POE).

The HD-TXA-4KZ-101-1G can be configured and controlled only when it is used with a DMPS Lite switcher. The web interface of the switcher can be used to configure the HD-TXA-4KZ-101-1G. In addition, control system programming and .AV Framework™ software support of the HD-TXA-4KZ-101-1G is hosted by the switcher.

4K60 4:4:4 and HDR Support

The HD-TXA-4KZ-101-1G supports video resolutions up to 4K60 with 4:4:4 color sampling. HDR10, HDR10+, and Dolby Vision® video formats are also supported.²

Analog Audio Embedding

The analog audio input port of the HD-TXA-4KZ-101-1G enables a balanced/unbalanced stereo audio source to be embedded with the video signal from the HDMI input. An audio selection push button is provided to switch between analog and HDMI audio inputs as desired. The audio selection push button is functional only when the HD-TXA-4KZ-101-1G is used with a DM Lite 4K60 4:4:4 receiver or a DMPS Lite HD-PS Series switcher.

One-Gang Wall Plate Design

The HD-TXA-4KZ-101-1G is designed to mount into a 1-gang U.S. electrical box or plaster ring (not included). The HD-TXA-4KZ-101-1G can receive power from the remote DM Lite receiver (surface mountable only) or DMPS Lite switcher.³

DM Lite® 4K60 4:4:4 Transmitter for HDMI® and Analog Audio Signal Extension over CATx Cable, Wall Plate

Specifications

Video

Input Signal Type	HDMI® with HDR10, HDR10+, Dolby Vision®, Deep Color, and 4K60 4:4:4 support ² (DVI and Dual-Mode DisplayPort™ interface compatible ⁴)
Output Signal Type	DM Lite® with HDR10, HDR10+, Dolby Vision, Deep Color, and 4K60 4:4:4 support ²
Copy Protection	HDCP 2.3
Resolutions	Common resolutions are listed in the following table.

Scan Type	Resolution	Frame Rate	Color Sampling	Color Depth
Progressive	4096x2160 DCI 4K & 3840x2160 4K UHD	24 Hz	4:4:4	12 bit
		30 Hz	4:4:4	12 bit
		60 Hz	4:2:2	12 bit
		60 Hz	4:4:4	8 bit
Progressive	2560x1600 WQXGA	60 Hz	4:4:4	8 bit
		1920x1080 FHD 1080p	60 Hz	4:4:4
Interlaced	1920x1080 HD 1080i	30 Hz	4:4:4	12 bit

NOTE: The maximum supported resolution is 4K60 with 4:4:4 color sampling. Custom resolutions are supported at pixel clock rates up to 600 MHz.

Audio

Input Signal Type	HDMI, analog stereo
Output Signal Type	DM Lite
Digital Formats	Dolby Digital®, Dolby Digital EX, Dolby Digital Plus, Dolby® TrueHD, Dolby Atmos®, DTS®, DTS ES, DTS 96/24, DTS HD® High Res, DTS-HD Master Audio, DTS:X®, LPCM up to 8 channels
Analog Format	Stereo 2-channel
Analog-to-Digital Conversion	24-bit 48 kHz

Analog Performance

Frequency Response: 20 Hz to 20 kHz
 ±0.5 dB;
 S/N Ratio: >95 dB 20 Hz to 20 kHz
 A-weighted;
 THD+N: <0.005% @ 1 kHz;
 Stereo Separation: ≤80 dB

Communications

HDMI	HDCP 2.3, EDID, CEC pass-through
DM Lite	HDCP 2.3, EDID pass-through

Connectors

HDMI IN	(1) HDMI Type A connector, female; HDMI digital video/audio input; DVI and Dual-Mode DisplayPort interface compatible ⁴
DM LITE OUT	(1) 8-pin RJ-45 yellow connector, female, shielded; DM Lite output port for connection to a DM Lite receiver or DMPS Lite™ switcher ^{1,5}
24V 0.75A	(1) 2-pin 3.5 mm detachable terminal block; 24VDC power input; Optional power pack (sold separately, required only if the HD-TXA-4KZ-101-1G is used with a wall plate receiver) ³
AUDIO IN	(1) 5-pin 3.5 mm detachable terminal block; Balanced/unbalanced stereo line-level audio input; Input Impedance: 24k Ohms balanced/unbalanced; Maximum Input Level: 4 Vrms balanced, 2 Vrms unbalanced
Ground	(1) Chassis ground lug

Controls and Indicators

LINK	(1) Green LED, indicates that a DM Lite link is established.
PWR	(1) LED, indicates that power is being applied to the device. Amber indicates that the device is booting. Green indicates that the device is operational.
AUDIO SELECT	(1) Push button, enables selection of HDMI or analog audio
AUDIO, HDMI IN	(1) Green LED, indicates that HDMI audio is selected
AUDIO IN	(1) Green LED, indicates that analog audio is selected

DM Lite® 4K60 4:4:4 Transmitter for HDMI® and Analog Audio Signal Extension over CATx Cable, Wall Plate

HDMI IN	(1) Green LED, indicates that the device is receiving an HDMI signal
DM LITE OUT	(2) LEDs on RJ-45 connector. Green indicates that a DM Lite link is established. Flashing amber indicates non-HDCP video, and solid amber indicates HDCP video.

Power

Power Pack (Optional)	Input: 100-240VAC Output: 24VDC 0.75A Model: PW-2407WUL (sold separately, required only if the HD-TXA-4KZ-101-1G is used with a wall plate receiver) ³
------------------------------	---

Environmental

Temperature	32° to 104°F (0° to 40°C)
Humidity	20% to 90% RH (non-condensing)

Construction

Composition	Metal housing and bracket with black polycarbonate front label overlay
Mounting	Mounts in a 1-gang (or larger) 2-1/4 inch (57 mm) deep U.S. electrical box or plaster ring (not included)
Faceplate	Requires a decorator style faceplate (FP-G series, sold separately)

Dimensions

Height	4.12 in. (105 mm)
Width	1.72 in. (44 mm)
Depth	2.26 in. (57 mm)

Weight

5.39 oz (153 g)

Compliance

Regulatory Model: M202047003

Intertek® Listed for US and Canada, CE, IC, FCC Part 15 Class B digital device

To search for product certificates, refer to support.crestron.com/app/certificates.

Model

HD-TXA-4KZ-101-1G-B

DM Lite® 4K60 4:4:4 Transmitter for HDMI® and Analog Audio Signal Extension over CATx Cable, Wall Plate, Black

Available Accessories

For a list of available accessories, visit the [HD-TXA-4KZ-101-1G-B](#) product page.

Notes:

- For DM Lite connections, use Crestron DM-CBL-8G, Crestron DM-CBL-ULTRA, or third-party CAT5e or higher cable. For information about the maximum transmission distance for each cable type, refer to [Online Help Answer ID 1001567](#).

To safeguard against unpredictable environmental electrical noise that may impact performance at resolutions above 1080p, shielded cable and connectors are recommended for all applications and are required when bundling multiple cables in a wire run. Cables are sold separately.
- When a DM Lite wall plate transmitter is paired with a DM Lite surface-mountable receiver, the power pack included with the receiver is used to power both devices.

When a DM Lite transmitter is paired with a DMPS Lite switcher, the switcher provides power to the DM Lite transmitter.

If a DM Lite wall plate transmitter is paired with a DM Lite wall plate receiver, the devices must be powered independently by a [PW-2407WUL](#) power pack (sold separately) for each device. A wall plate transmitter and wall plate receiver cannot provide power to the remote device with which it is paired.
- The HDMI input requires an appropriate adapter or interface cable to accommodate a Dual-Mode DisplayPort or DVI signal. CBL-HDI-DVI interface cables are sold separately.
- Examples of supported DM Lite 4K60 4:4:4 receivers are the HD-RX-4KZ-101, HD-RXA-4KZ-101, HD-RXC-4KZ-101, and HD-RXCA-4KZ-101. Supported DM Lite 4K60 4:2:0 receivers are the HD-RX-101-C-E, HD-RXC-101-C-E, HD-RX-201-C-E, HD-RX-101-C-1G-E, and HD-RXC-101-C-1G-E. Supported DMPS Lite switchers are the HD-PS622, HD-PS621, HD-PS402, HD-PS401, and HD-RX-4K-210-C-E (-POE).

DM Lite® 4K60 4:4:4 Transmitter for HDMI® and Analog Audio Signal Extension over CATx Cable, Wall Plate

This product may be purchased from select authorized Crestron dealers and distributors. To find a dealer or distributor, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/How-To-Buy/Find-a-Representative or contact us for additional information by visiting www.crestron.com/contact/our-locations for your local contact.

This product is covered under the Crestron standard limited warranty. Refer to www.crestron.com/warranty for full details.

The specific patents that cover Crestron products are listed online at patents.crestron.com.

Certain Crestron products contain open-source software. For specific information, please visit www.crestron.com/opensource.

Crestron, the Crestron logo, .AV Framework, DM Lite, and DMPS Lite are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Dolby, Dolby Atmos, Dolby Digital, and Dolby Vision are either trademarks or registered trademarks of Dolby Laboratories in the United States and/or other countries. DTS, DTS HD, and DTS:X are either trademarks or registered trademarks of DTS, Inc. in the United States and/or other countries. HDMI and the HDMI logo are either trademarks or registered trademarks of HDMI Licensing LLC in the United States and/or other countries. Intertek and the Intertek logo are either trademarks or registered trademarks of Intertek Group in the United States and/or other countries. DisplayPort is either a trademark or registered trademark of Video Electronics Standards Association in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography.

HDMI

Specifications are subject to change without notice.

©2022 Crestron Electronics, Inc.

Rev 06/03/22

DM Lite® 4K60 4:4:4 Transmitter for HDMI® and Analog Audio Signal Extension over CATx Cable, Wall Plate

