

C2N-DBN12

Decorator Numeric Keypad

- > A decorator-style wall mount keypad with 12 buttons
- > Includes pre-labeled button caps for numeric entry applications
- > Red LED feedback indicators
- > Fits standard electrical gang boxes and faceplates
- > Available in smooth almond, black, and white finishes
- > Cresnet® wired communications

The Decorator Series C2N-DBN12 Numeric Keypad is an optional complement to the [C2N-DBF12](#) Function Keypad, allowing for enhanced control of a Crestron® Multiroom AV distribution system with direct numeric entry for the selection of channels and tracks. It also works well for pass code entry applications.

The C2N-DBN12 is identical to the [C2N-DB12](#) 12-Button Decorator Keypad except that it includes a set of 12 button caps pre-labeled for numeric entry applications.

Please note, the almond smooth (-A-S) and white smooth (-W-S) finishes currently offered are not the same as on older almond (A) and white (W) models. When ordering, please be sure to specify the model number exactly as shown in the price list or on the [“Models & Accessories”](#) tab. If you require buttons or keypads to match the older almond or white finishes, please contact your Crestron representative.



SPECIFICATIONS

Buttons

Keypad Buttons: (12) programmable pushbuttons

Button Caps: Includes 12 pre-labeled button caps: numerals “1” thru “9” and “0”, “CLEAR” and “ENTER”

Indicators

Feedback: (1 per button) red LED, programmable, software-adjustable intensity

Connectors

NET: (1) 4-pin 3.5mm detachable terminal block; Cresnet slave port, connects to Cresnet control network

Power Requirements

Cresnet Power Usage: 3 Watts (0.125 Amps @ 24 Volts DC)

Environmental

Temperature: 32° to 113°F (0° to 45°C)

Humidity: 10% to 90% RH (non-condensing)

Construction

Chassis: Plastic

Mounting: Mounts in a 1-gang or larger electrical box or mud ring
Faceplate: Requires decorator style faceplate (not included)

Dimensions

Height: 4.16 in (106 mm) without faceplate

Width: 1.79 in (46 mm) without faceplate

Depth: 1.53 in (39 mm)

Weight

2.6 oz (75 g)

MODELS & ACCESSORIES

Available Models

C2N-DBN12-A-S: Decorator Numeric Keypad, Almond Smooth

C2N-DBN12B: Decorator Numeric Keypad, Black Smooth

C2N-DBN12-W-S: Decorator Numeric Keypad, White Smooth

Available Accessories

CRESNET-NP: Cresnet® Control Cable, non-plenum

CRESNET-P: Cresnet® Control Cable, plenum

CRESNET-HP-NP: Cresnet® “High-Power” Control Cable, non-plenum

CCR-L-1: Crestron® Color Ring

C2N-DBN12 Decorator Numeric Keypad

Notes:

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/salesreps or by calling 800-237-2041.

The specific patents that cover Crestron products are listed online at: patents.crestron.com.

Crestron, the Crestron logo, and Cresnet are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography. Specifications are subject to change without notice. ©2013 Crestron Electronics, Inc.

