

Architectural Series Faceplates: TPS-FPAR2000L

Description

Architectural Series Faceplates bring a clean, updated look to the TPS-2000L series touchpanels. They feature machined aluminum construction with a stylish shape that is a pleasing alternative to traditional flat faceplates, and they are available in a variety of finishes including stainless steel, anodized black, and the standard white and almond. (Refer to the table below.)


Use the following procedure to install the new faceplates. (Refer to the illustration below.)

1. Lift the existing faceplate off the touchpanel. If necessary, use a small flat-bladed screwdriver between the faceplate and the mounting surface, using a gentle twist to free the faceplate.
2. Position the new faceplate over the touchpanel and firmly press the faceplate until it snaps into position.

| MODEL NUMBER | FINISH* |
|---------------------------|------------------------------|
| TPS-FPAR-2000L-A | Almond |
| TPS-FPAR-2000L-A-NB | Almond, W/O Buttons |
| TPS-FPAR-2000L-A/BLK | Anodized Black |
| TPS-FPAR-2000L-A/BLK-NB | Anodized Black, W/O Buttons |
| TPS-FPAR-2000L-S/STEEL | Stainless Steel |
| TPS-FPAR-2000L-S/STEEL-NB | Stainless Steel, W/O Buttons |
| TPS-FPAR-2000L-W | White |
| TPS-FPAR-2000L-W-NB | White, W/O Buttons |

**Aluminum composition; may not be suitable for sterile environment.*

CAUTION: Do not put pressure on the touchscreen when removing/installing faceplates.



Further Inquiries

If you cannot locate specific information or have questions after reviewing this guide, please take advantage of Crestron's award winning customer service team by calling the Crestron corporate headquarters at 1-888-CRESTRON [1-888-273-7876]. For assistance in your local time zone, refer to the Crestron website (www.crestron.com) for a listing of Crestron worldwide offices.

You can also log onto the online help section of the Crestron website to ask questions about Crestron products. First-time users will need to establish a user account to fully benefit from all available features.

Return and Warranty Policies

Merchandise Returns / Repair Service

1. No merchandise may be returned for credit, exchange, or service without prior authorization from CRESTRON. To obtain warranty service for CRESTRON products, contact the factory and request an RMA (Return Merchandise Authorization) number. Enclose a note specifying the nature of the problem, name and phone number of contact person, RMA number, and return address.
2. Products may be returned for credit, exchange, or service with a CRESTRON Return Merchandise Authorization (RMA) number. Authorized returns must be shipped freight prepaid to CRESTRON, 6 Volvo Drive, Rockleigh, N.J., or its authorized subsidiaries, with RMA number clearly marked on the outside of all cartons. Shipments arriving freight collect or without an RMA number shall be subject to refusal. CRESTRON reserves the right in its sole and absolute discretion to charge a 15% restocking fee, plus shipping costs, on any products returned with an RMA.
3. Return freight charges following repair of items under warranty shall be paid by CRESTRON, shipping by standard ground carrier. In the event repairs are found to be non-warranty, return freight costs shall be paid by the purchaser.

CRESTRON Limited Warranty

CRESTRON ELECTRONICS, Inc. warrants its products to be free from manufacturing defects in materials and workmanship under normal use for a period of three (3) years from the date of purchase from CRESTRON, with the following exceptions: disk drives and any other moving or rotating mechanical parts, pan/tilt heads and power supplies are covered for a period of one (1) year; touchscreen display and overlay components are covered for 90 days; batteries and incandescent lamps are not covered.

This warranty extends to products purchased directly from CRESTRON or an authorized CRESTRON dealer. Purchasers should inquire of the dealer regarding the nature and extent of the dealer's warranty, if any.

CRESTRON shall not be liable to honor the terms of this warranty if the product has been used in any application other than that for which it was intended, or if it has been subjected to misuse, accidental damage, modification, or improper installation procedures. Furthermore, this warranty does not cover any product that has had the serial number altered, defaced, or removed.

This warranty shall be the sole and exclusive remedy to the original purchaser. In no event shall CRESTRON be liable for incidental or consequential damages of any kind (property or economic damages inclusive) arising from the sale or use of this equipment. CRESTRON is not liable for any claim made by a third party or made by the purchaser for a third party.

CRESTRON shall, at its option, repair or replace any product found defective, without charge for parts or labor. Repaired or replaced equipment and parts supplied under this warranty shall be covered only by the unexpired portion of the warranty.

Except as expressly set forth in this warranty, CRESTRON makes no other warranties, expressed or implied, nor authorizes any other party to offer any warranty, including any implied warranties of merchantability or fitness for a particular purpose. Any implied warranties that may be imposed by law are limited to the terms of this limited warranty. This warranty statement supercedes all previous warranties.

Trademark Information

All brand names, product names, and trademarks are the sole property of their respective owners. Windows is a registered trademark of Microsoft Corporation. Windows95/98/Me/XP and WindowsNT/2000 are trademarks of Microsoft Corporation.